

ENGINEERING DATA SHEET

SERIES 9123

CONTACTOR
3 PST/NO, 25 AMP



Balanced armature design

Hermetically sealed

Contact arrangement

3 PST/NO - DM

Meets the standards and requirements of

MIL-PRF-6106

PRINCIPLE TECHNICAL CHARACTERISTICS

Contacts rated at

**28 Vdc; 115 Vac, 400 Hz,
1Ø 115/200 Vac, 400 Hz,
3Ø**

Weight

570 g ±10%

Dimensions

**83.8mm x 94.7mm x
63.5mm**

Special units available upon request, including models with auxiliary contacts.

APPLICATION NOTES:

[101](#)

[102](#)

[103F](#)

[007](#)

CONTACT ELECTRICAL CHARACTERISTICS

Contact rating per pole and load type [1]	Load current in Amps				
	28 Vdc	115 Vac 400 Hz	115/200 Vac 400 Hz 3Ø	115 Vac 60 Hz [5]	440 Vac 60 Hz [5] DELTA
Resistive	25	25	25	15	12.5
Inductive [6]	25	25	25	15	12.5
Motor	25	25	25	7	10
Intermediate current	2.5	2.5	2.5	-	-



Featuring **LEACH®** power and control solutions
www.esterline.com

AMERICAS

6900 Orangethorpe Ave.
P.O. Box 5032
Buena Park, CA 90622

Tel: (01) 714-736-7599
Fax: (01) 714-670-1145

EUROPE

2 Rue Goethe
57430 Sarralbe
France

Tel: (33) 3 87 97 31 01
Fax: (33) 3 87 97 96 86

ASIA

Units 602-603 6/F Lakeside 1
No.8 Science Park West Avenue
Phase Two, Hong Kong Science Park
Pak Shek Kok, Tai Po, N.T.
Hong Kong

Tel: (852) 2 191 3830
Fax: (852) 2 389 5803

Data sheets are for initial product selection and comparison. Contact Esterline Power Systems prior to choosing a component.

COIL CHARACTERISTICS (Vdc)**SERIES 9123**

CODE	Vdc	115 Vac 60/400 Hz	Suppressed Vdc [2]
Nominal operating voltage	28	115	28
Maximum operating voltage	29	124	29
Pick-up voltage, max.			
- Nominal	18	90	18
- High temp test	21	100	21
- Continuous current test	22.5	104	22.5
Drop-out voltage, max.			
	7	40	7
Coil resistance ohms $\pm 10\%$ at +25° C	50	-	50
Coil current max. mA at +25° C	-	200	-

GENERAL CHARACTERISTICS

Temperature range	-70°C to +125°C
Minimum operating cycles (life) at rated load	50,000
Minimum operating cycles (life) at 25% rated load	100,000
Dielectric strength at sea level	
- Coil to case	DC 1,250 Vrms AC 1,500 Vrms
- Auxiliary contacts	DC 1,250 Vrms AC 1,500 Vrms
- All other points	DC 1,250 Vrms AC 1,800 Vrms
Dielectric strength at altitude 80,000 ft	700 Vrms (Coil 500 Vrms)
Insulation resistance (at 500 Vdc) minimum	100 M Ω min
Sinusoidal vibration (55-1500 Hz)	15G
Shock (6-9 millisecond duration)	50G
Maximum contact opening time under shock or vibration	2 ms
Operate time at nominal voltage	
- DC	25 ms max
- AC	30 ms max
Release time at nominal voltage	
- DC	10 ms max
- AC	50 ms max
Contact bounce at nominal voltage	2 ms max [1]
Weight, max.	1.25 lb

RELAY NUMBERING SYSTEM

SERIES 9123


LEACH PART NO.	DESCRIPTION	MS NUMBER	MOUNTING STYLE [4]	SCHEMATIC DIAGRAM [4]
9123-C7C4-002	3 PST/NO, 25 AMP, DC COIL	MS27997-D1	1	1
9123-C7D3-002	3 PST/NO, 25 AMP, AC COIL	MS27997-A1	1	1
9123-1Z-C7C4-002	3 PST/NO, 25 AMP, DC COIL, AUX CONTACT	MS27997-D2	1	2
9123-1Z-C7D3-002	3 PST/NO, 25 AMP, AC COIL, AUX CONTACT	MS27997-A2	1	2
9123-8069	3 PST/NO, 25 AMP, DC COIL	MS24143-D1 [3]	2	1
9123-8070	3 PST/NO, 25 AMP, AC COIL	MS24143-A1 [3]	2	1
9123-8071	3 PST/NO, 25 AMP, DC COIL, AUX CONTACT	MS24143-D2 [3]	2	2
9123-8072	3 PST/NO, 25 AMP, AC COIL, AUX CONTACT	MS24143-A2 [3]	2	2
9123-10394	3 PST/NO, 25 AMP, DC SUPPRESSED COIL	-	1	3
9123-10395	3 PST/NO, 25 AMP, DC SUPPRESSED COIL, AUX CONTACT	-	1	4
9123-10396	3 PST/NO, 25 AMP, DC SUPPRESSED COIL	-	2	3
9123-10397	3 PST/NO, 25 AMP, DC SUPPRESSED COIL, AUX CONTACT	-	2	4

Special models available upon request, please contact factory.

NOTES


- [1] Auxiliary contact rating:
 Resistive and inductive: (28 Vdc or 115 Vac) 5 Amp
 Lamp: (28 Vdc or 115 Vac) 1 Amp
 Bounce at nominal voltage: .004 sec max
- [2] Coils have back EMF suppression to 42 volts.
- [3] MS numbers are for reference only. Relays are electrically and mechanically interchangeable except the height is less on the Leach relays similar to MS24143.
- [4] See the following pages for mounting styles and schematic diagram.
- [5] Ratings beyond MS requirements.
- [6] Inductive life is 20 percent of rated resistive load life.

MOUNTING STYLE 1




1 2 PLACES, FOR NON-AUXILIARY MODELS

MOUNTING STYLE 2




1 2 PLACES, FOR NON-AUXILIARY MODELS


SCHEMATIC DIAGRAM NO 1




SCHEMATIC DIAGRAM NO 2



SCHEMATIC DIAGRAM NO 3




SCHEMATIC DIAGRAM NO 4




STANDARD. TOLERANCE: ± .031

PART NUMBER: 001-8708-000



PART NUMBER: 001-1908-000



DERATING OF CONTACTS FOR DC VOLTAGES ABOVE NOMINAL RATING

To establish a standard for the derating of relay contacts is, at best, a subjective practice. Limitations are governed by the type of relay, contact gap, maximum voltage capabilities of the relay contact system, and the contact material.

The most common method is to derate the contacts by use of the Power Formula, using the known current and voltage.

This method is valid only for **Resistive Loads**, and is an approximation only; keeping in mind the limitations mentioned above.

$$\text{Power} = IE \text{ (Current x Voltage)}$$

$$I_2 E_2 = 2/3 I_1 E_1$$

Example:

A designer is working with a 55 volt DC system and has a relay rated at 10 amps resistive at 28 volts DC. What is the maximum current that can be switched at 55 Vdc.

$$I_1 = 10 \text{ Amperes}$$

$$E_1 = 28 \text{ VDC}$$

$$E_2 = 55 \text{ VDC}$$

$$I_2 = ? \text{ (Current ratings at 55 VDC Resistive)}$$

$$I_2 E_2 = 2 I_1 E_1 / 3$$

$$I_2 = 2 I_1 E_1 / E_2 \times 3$$

$$= 2 (10 \times 28) / 55 \times 3$$

$$= 560 / 165$$

$$I_2 = 3.4 \text{ Amperes at 55VDC}$$

In addition, the user should always be concerned about the following:

1. Derating contacts that are rated for less than 10 Amperes at nominal voltage.
2. Derating contacts for use in system voltages above 130 Volts DC

RELAYS AND TEMPERATURE VARIATIONS

Most relay parameters are specified as maximum values over the rated temperature range of the specific relay. Users often find that key parameters differ significantly at ambient temperature (20-25°C) and sometimes fall into the trap of specifying their system around these ambient parameters. Additionally the actual temperature experienced by the relay can be far in excess of existing ambient temperatures due to the heat generated by the coil current and the contact load. Figure 1 is the summary of temperature effects on relay electrical characteristics.

Temperature	Resistance	Current	Operating Voltage	Release Voltage	Operate Time	Release Time
Increase	UP	DOWN	UP	UP	UP	UP
Decrease	DOWN	UP	DOWN	DOWN	DOWN	DOWN

Fig. 1

The following formulas are sometimes useful in calculating the effects shown above.

1. Change in coil resistance due to change of ambient temperature can be calculated by the following formula.

$$R = R_{20} [1 + .0039 (T-20)]$$

Where: R = Coil resistance at given temperature

R_{20} = Coil resistance at 20°C

T = °C Ambient temperature

"Rule of Thumb" : For each 10°C change of temperature, coil resistance will change approximately 4%.

2. High and low temperature pick up voltage:

$$E_2 = E_1 K_2,$$

Where: E_2 = Pick Up Voltage at T_2 temperature

E_1 = Pick Up Voltage at 20°C

K_2 = Coefficient of correction found on the graph in Fig. 2 at T_2

3. Calculation of coil temperature rise when R initial and R final are known:

$$\Delta T = (234.5 + T_1) (R_2/R_1 - 1)$$

ΔT = Temperature rise (°C)

T_1 = Initial temperature (°C)

R_1 = Initial resistance (Ohms)

R_2 = Final resistance (Ohms)

$$R_2 = K_2 R_1$$

Temperature can also be found by making the R_2/R_1 ratio = the coefficient of correction graph in Fig. 2, and then finding the corresponding temperature.

TEMPERATURE CORRECTION CHART FOR RESISTANCE





Fig. 2

EXAMPLE:

Catalog indicates coil resistance of 290 ohm at 25°C. What is the value at 125°C?

From the chart: $290 \times 1.39 = 403.31$ Ohms.

CURVES FOR DC VOLTAGES ABOVE NORMAL RATING: RESISTIVE LOAD ONLY
(without arc suppression)



SUPPRESSOR DEVICES FOR RELAY COILS

The inductive nature of relay coils allows them to create magnetic forces which are converted to mechanical movements to operate contact systems. When voltage is applied to a coil, the resulting current generates a magnetic flux, creating mechanical work. Upon deenergizing the coil, the collapsing magnetic field induces a reverse voltage (also known as back EMF) which tends to maintain current flow in the coil. The induced voltage level mainly depends on the duration of the deenergization. The faster the switch-off, the higher the induced voltage.

All coil suppression networks are based on a reduction of speed of current decay. This reduction may also slow down the opening of contacts, adversely affecting contact life and reliability. Therefore, it is very important to have a clear understanding of these phenomena when designing a coil suppression circuitry.

Typical coil characteristics

On the graph below, the upper record shows the contacts state. (High level NO contacts closed, low level NC contacts closed, intermediate state contact transfer). The lower record shows the voltage across the coil when the current is switched off by another relay contact.

The surge voltage is limited to -300V by the arc generated across contact poles. Discharge duration is about 200 microseconds after which the current change does not generate sufficient voltage. The voltage decreases to the point where the contacts start to move, at this time, the voltage increases due to the energy contained in the NO contact springs. The voltage decreases again during transfer, and increases once more when the magnetic circuit is closed on permanent magnet.


Operating times are as follows:

Time to start the movement 1.5ms

Total motion time 2.3ms

Transfer time 1.4ms

Contact State



Types of suppressors:

Passive devices.

The resistor capacitor circuit

It eliminates the power dissipation problem, as well as fast voltage rises. With a proper match between coil and resistor, approximate capacitance value can be calculated from:

$C = 0.02 \times T / R$, where

T = operating time in milliseconds

R = coil resistance in kiloOhms

C = capacitance in microFarads


The series resistor must be between 0.5 and 1 times the coil resistance. Special consideration must be taken for the capacitor inrush current in the case of a low resistance coil.

The record shown opposite is performed on the same relay as above. The operation time becomes:

- time to start the movement 2.3ms

- transfer time 1.2ms

The major difficulty comes from the capacitor volume. In our example of a relay with a 290Ω coil and time delay of 8 ms, a capacitance value of $C=0.5 \mu\text{F}$ is found. This non polarized capacitor, with a voltage of 63V minimum, has a volume of about 1cm^3 . For 150V, this volume becomes 1.5 cm^3 .



The bifilar coil

The principle is to wind on the magnetic circuit of the main coil a second coil shorted on itself. By a proper adaptation of the internal resistance of this second coil it is possible to find an acceptable equilibrium between surge voltage and reduction of the opening speed. To be efficient at fast voltage changes, the coupling of two coils must be perfect. This implies embedded windings. The volume occupied by the second coil reduces the efficiency of the main coil and results in higher coil power consumption. This method cannot be applied efficiently to products not specifically designed for this purpose.

The resistor (parallel with the coil)

For efficient action, the resistor must be of the same order of magnitude as the coil resistance. A resistor 1.5 times the coil resistance will limit the surge to 1.5 times the supply voltage. Release time and opening speed are moderately affected. The major problem is the extra power dissipated.

Semi-conductor devices

The diode


It is the most simple method to totally suppress the surge voltage. It has the major disadvantage of the higher reduction of contact opening speed. This is due to the total recycling, through the diode, of the energy contained in the coil itself. The following measurement is performed once again on the same relay. Operation times are given by the upper curve:

- time to start the movement 14ms
- transfer time 5ms

These times are multiplied by a coefficient from 4 to 8.

The lower curve shows the coil current. The increase prior to NO contact opening indicates that the contact spring dissipates its energy. At the opening time the current becomes constant as a result of practically zero opening speed.

Due to this kind of behavior, this type of suppression must be avoided for power relays. For small relays which have to switch low currents of less than 0.2 A, degradation of life is not that significant and the method may be acceptable.



The diode + resistor network

It eliminates the inconvenience of the resistor alone, explained above, and it limits the action of a single diode. It is now preferred to use the diode + zener network.

The diode + zener network

Like the resistor, the zener allows a faster decurrent decay. In addition it introduces a threshold level for current conduction which avoids the recycling of energy released during contact movement.

The lower curve on the opposite record demonstrates those characteristics. Voltage limitation occurs at 42V. The two voltage spikes generated by internal movement are at lower levels than zener conduction. As a result, no current is recycled in the coil.

The opening time phases are as follows:

- time to start the movement 2.6ms
- total motion time 2.4ms
- transfer time 1.4ms

The release time is slightly increased. The contacts' opening speed remains unchanged.

