



Miniature Incandescent Lamps

T-1 Bulb Sub-Midget Flanged Base



Mfr.'s Type	Design Volts	Design Amps	MSCD
6839AS25	28	0.025	0.15


T-1 Bulb Wire Terminals



Mfr.'s Type	Design Volts	Design Amps	MSCD
6832AS25*	5	0.06	0.05

*Aged & selected for $\pm 25\%$ MSCD tolerance


T-1 Bulb Axial Wire Terminals



Mfr.'s Type	Design Volts	Design Amps	MSCD
7154AS15*	5	0.115	0.15


*Aged & selected for $\pm 15\%$ MSCD tolerance

T-1½ Bulb S.C. Midget Flange Base




Mfr.'s Type	Design Volts	Design Amps	MSCD
328	6	0.2	0.34
381	6.3	0.2	0.4
394	12	0.04	0.12
330	14	0.08	0.5
382	14	0.08	0.3
327	28	0.04	0.34
387	28	0.04	0.3

T-1½ Bulb Wedge Base




Mfr.'s Type	Design Volts	Design Amps	MSCD
56	5	0.115	0.15
79	6	0.2	0.6
86	6.3	0.2	0.4
73	14	0.08	0.3
37	14	0.09	0.5
74	14	0.1	0.7
85	28	0.04	0.3
17	28	0.065	0.65

T-1½ Bulb Midget Grooved Base




Mfr.'s Type	Design Volts	Design Amps	MSCD
337	6	0.2	0.6
386	14	0.08	0.3
334	28	0.04	0.34
388	28	0.04	0.3

T-1½ Bulb Bi-Pin Base




Mfr.'s Type	Design Volts	Design Amps	MSCD
7371	12	0.04	0.1
7382	14	0.08	0.3
7327	28	0.04	0.34
7387	28	0.04	0.3

T-2 Bulb BA7s Base




Mfr.'s Type	Design Volts	Design Amps	MSCD
3798	6	0.1	0.2
3799	6	0.2	0.6
3898	12	0.17	0.6
3899	24	0.125	0.6

T-2 Bulb Slide Base #6




Mfr.'s Type	Design Volts	Design Amps	EFC
51A	10	0.035	275
16ESB	16	0.04	800
24CSB	24	0.017	100
24ESB	24	0.04	850
28ESB	28	0.04	1500
48ESB	48	0.04	3000

T-2 Bulb Slide Base #5




Mfr.'s Type	Design Volts	Design Amps	EFC
6PSB	6	0.14	550
12PSB	12	0.17	2000
24PSB	24	0.073	3000
28PSB	28	0.04	1600
48PSB	48	0.05	1800
60PSB	60	0.05	1800
120PSB	120	0.025	1000

T-2 Bulb Slide Base #3




Mfr.'s Type	Design Volts	Design Amps	EFC
24E	24	0.035	600
24X	24	0.035	600
48C	48	0.035	400

T-2 Bulb Wire Terminals




Mfr.'s Type	Design Volts	Design Amps	EFC
12PS	12	0.17	2000
120PS	120	0.025	1000

T-2½ Bulb Miniature Bayonet Base




Mfr.'s Type	Design Volts	Design Amps	EFC
12MB	12	0.17	0.35
24MB	24	0.07	0.5
28MB	28	0.05	0.29
48MB	48	0.05	0.70
60MB	60	0.05	0.73
90MB	90	0.03	0.37
120MB	120	0.025	0.36

T-3 Bulb With End Caps




Mfr.'s Type	Design Volts	Design Amps	MSCD
211-2	12.8	0.97	12
214-2	13.5	0.52	4
212-2	13.5	0.74	6

T-3 Bulb With Rigid Loops



Mfr.'s Type	Design Volts	Design Amps	MSCD
561	12.8	0.97	12

T-3½ Bulb Miniature Bayonet Base



Mfr.'s Type	Design Volts	Design Amps	MSCD
1850	5	0.09	0.25
47	6.3	0.15	0.5
755	6.3	0.15	0.33
1847	6.3	0.15	0.38
44	6.3	0.25	0.9
1816	13	0.33	3
756	14	0.08	0.31
1815	14	0.2	1.4
1891	14	0.24	2
1889	14	0.27	2
1893	14	0.33	2
1892	14.4	0.12	0.75
1819	28	0.04	0.33
1829	28	0.07	1
757	28	0.08	0.62
1820	28	0.1	1.6
313	28	0.17	3.5
1864	28	0.17	3
1822	36	0.1	2.1
1835	55	0.05	1.1